

Splice Tape



A SIKA COMPANY

GENERAL DESCRIPTION

Splice Tape is a black, pressure sensitive, fully cured, double-sided, butyl tape. Splice Tape is supplied on a high strength, specially formulated release liner in a 4 inch wide by 100 foot long roll. Splice Tape is 0.035 inch thick. It can be applied at temperatures 0° F to 200° F and contains no VOCs. It has a very high tack, peel, and shear strength with excellent heat and water resistance.

BASIC USE

Hydrotech Splice Tape is designed to be used with Hydrotech VOC-complaint Splice Tape Primer to bond the laps of Flex-Flash UN uncured neoprene flashing together when VOC regulations prohibit the use of the standard Splicing Cement contact adhesive.

APPLICATION

- The adjacent sheets of Flex-Flash UN must be installed to provide a minimum 3 inch wide lap. The mating surfaces of the Flex-Flash UN must be clean and free of any contaminants and the polyethylene release sheet must be removed from the Flex-Flash UN.
- Thoroughly stir the Splice Tape Primer before and during use to completely disperse any settled materials.
- Apply the Splice Tape Primer with a roller or brush to the area of Flex-Flash UN membrane to be seamed on both mating surfaces of membrane at a rate of 350-400 sqft/gallon each surface. 1 gallon of Primer would be enough to treat both mating surfaces of Flex-Flash UN for approximately 6 rolls of Splice Tape (600 ln.ft.).
- Allow the Splice Tape Primer to dry on both membrane surfaces so that it does not stick or string-up to a dry finger touch.
- Install the Splice Tape immediately after the Primer has dried to prevent dust contamination and promote adhesion in colder weather.
- Unroll a small section of Splice Tape and line up an edge of the Tape with the inside edge of the Flex-Flash UN bottom sheet. Press the Tape down to the bottom sheet using firm, even hand pressure on the release liner.
- Roll the Splice Tape with a 2 inch wide steel hand roller to ensure 100% contact and work out any air pockets.
- Remove the release liner and fold the top sheet of Flex-Flash UN down into the exposed Tape, avoiding air pockets and wrinkles while pressing down using firm, even hand pressure. A maximum of 1/4 inch of Splice Tape should extend beyond the edge of the top sheet of membrane.
- Immediately roll the lap with a 2 inch wide steel hand roller using positive pressure. Roll across the lap edge, not parallel to it.

NOTES/PRECAUTIONS

- To achieve proper adhesion at ambient temperatures below 40°F, Splice Tape must be stored near room temperature and kept at 40°F or higher during use. In addition, a hot air gun should be used to heat;
- the primed area as the Splice Tape is applied.
- the lap area prior to final rolling.
- When it is necessary to continue a Tape application after reaching the end of a roll or when cut, overlap subsequent Tape applications 1 inch minimum.
- Lap Sealant is not required along the exposed edge of Flex-Flash UN when the Splice Tape extends at least 1/4 inch past the edge.
- Prolonged storage temperatures >90°F may impact product shelf life. Onsite, keep Splice Tape rolls boxed in a shaded, dry area until ready to use.
- Condensation may form on freshly applied Primer when ambient temperature is near the dew point. In such conditions, stop application, allow area to dry, and re-apply a thin coat of Primer when conditions allow.

TECHNICAL DATA

PROPERTY	RESULTS
COLOR	Black
PENETRATION	100/130 mm
SOLVENTS	2 rolls/case (minimum order 1 case)
VOLATILITY	0
SHELF LIFE	12 months

LEED INFORMATION

	Credit 4	Credit 5
Recycled Content (% by weight)	0	
Manufacture Location		Ashland, OH
Extraction/Harvesting Location		Ashland, OH
VOC Content (g/L)		0

This information is intended only for general conceptual purposes. It is based on data and knowledge considered to be true and correct. It is offered for the user's consideration, investigation and verification and is not intended to substitute for the advice provided by appropriate professionals. Hydrotech assumes no liability for the use of this information. The determination of the suitability and applicability of this information is the sole responsibility of the user.